

Model	V/A/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
DX400E	400VA/240W	00:29:07 h	00:11:30 h	00:05:25 h	00:03:30 h	12V, 4.5AH * 1
DX600E	600VA/360W	00:26:55 h	00:09:50 h	00:05:19 h	00:02:50 h	12V, 7AH * 1
DX800E	800VA/480W	00:26:54 h	00:08:10 h	00:04:30 h	00:02:10 h	12V, 8.5AH * 1

Model	V/A/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
BS450ELCD	450VA/270W	00:23:51 h	00:09:46 h	00:04:53 h	00:02:45 h	12V, 4.5AH * 1
BS650ELCD	650VA/390W	00:24:27 h	00:10:25 h	00:04:47 h	00:02:35 h	12V, 7AH * 1
BS850ELCD	850VA/510W	00:22:54 h	00:07:54 h	00:03:18 h	00:01:30 h	12V, 8.5AH * 1

Model	V/A/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
BR450E	450VA/270W	00:20:40 h	00:08:05 h	00:02:55 h	00:01:10 h	12V, 4.5AH * 1
BR650E	650VA/390W	00:26:00 h	00:09:15 h	00:04:00 h	00:01:35 h	12V, 7AH * 1
BR850E	850VA/510W	00:21:15 h	00:08:10 h	00:03:25 h	00: 01:16 h	12V, 8.5AH * 1

Model	V/A/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
BR450ELCD	450VA/270W	00:20:40 h	00:08:05 h	00:02:55 h	00:01:10 h	12V, 4.5AH * 1
BR650ELCD	650VA/390W	00:26:00 h	00:09:15 h	00:04:00 h	00:01:35 h	12V, 7AH * 1
BR850ELCD	850VA/510W	00:21:15 h	00:08:10 h	00:03:25 h	00: 01:16 h	12V, 8.5AH * 1

Model	V/A/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
Value 400E-GP	400VA/240W	00:25:00 h	00:09:30 h	00:04:00 h	00:01:35 h	12V, 4.5AH * 1
Value 600E-GP	600VA/360W	00:28:35 h	00:10:10 h	00:04:40 h	00:01:50 h	12V, 7AH * 1
Value 800E-GP	800VA/480W	00:23:35 h	00:08:50 h	00:03:45 h	00:01:30 h	12V, 8.5AH *1
Value 1000E-GP	1000VA/530W	00:19:45 h	00:07:52 h	00:02:47 h	00:01:10 h	12V, 8.5AH *1
Value 1200ELCD-GP	1200VA/720W	00:28:35 h	00:10:10 h	00:04:40 h	00:02:30 h	12V, 7AH * 2
Value 1500ELCD-GP	1500VA/900W	00:25:50 h	00:09:25 h	00:04:20 h	00:02:10 h	12V, 8.5AH *2
Value 2200ELCD-GP	2200VA/1320W	00:18:30 h	00:07:10 h	00:02:50 h	00:01:20 h	12V, 9AH * 2

The runtimes for ValueE and ValueE-GP are identical

Model	V/A/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
CP1350EAVRLCD	1350VA/810W	00:31:56 h	00:09:29 h	00:05:13 h	00:02:03 h	12V, 8AH * 2
CP1500EAVRLCD	1500VA/900W	00:31:19 h	00:10:53 h	00:05:10 h	00:02:23 h	12V, 8.5AH * 2

Model	VA/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
OR1000ELCDRM1U	1000VA/600W	00:35:40 h	00:13:40 h	00:06:55 h	00:03:45 h	6V, 7AH * 4
OR1500ELCDRM1U	1500VA/900W	00:29:35 h	00:11:00 h	00:05:35 h	00:03:00 h	6V, 9AH * 4

Model	VA/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
PR750ELCDRT1U	750VA/500W	00:55:00 h	00:23:00 h	00:13:00 h	00:07:00 h	6V, 9AH * 4
PR1000ELCDRT1U	1000VA/670W	00:37:00 h	00:14:00 h	00:08:00 h	00:05:00 h	6V, 9AH * 4
PR1000ELCDRT2U	1000VA/700W	01:03:00 h	00:28:00 h	00:16:00 h	00:10:00 h	12V, 7AH* 4
PR1500ELCDRT2U	1500VA/1000W	00:44:00 h	00:18:00 h	00:09:30 h	00:06:00 h	12V, 7AH * 4
PR2200ELCDRT2U	2200VA/1600W	00:30:00 h	00:12:00 h	00:07:00 h	00:04:30 h	12V, 9AH * 4
PR3000ELCDRT2U	3000VA/2250W	00:18:30 h	00:08:00 h	00:04:00 h	00:02:30 h	12V, 9AH * 4
PR1000ELCDRTXL2U	1000VA/750W	01:18:00 h	00:32:00 h	00:18:30 h	00:13:00 h	12V, 9AH * 4
PR1500ELCDRTXL2U	1500VA/1125W	00:43:00 h	00:18:30 h	00:11:00 h	00:08:00 h	12V, 9AH * 4
PR2200ELCDRTXL2U	2200VA/1650W	00:28:30 h	00:11:30 h	00:07:00 h	00:04:00 h	12V, 9AH * 4
PR3000ELCDRTXL2U	3000VA/2400W	00:17:00 h	00:07:00 h	00:03:30 h	00:02:30 h	12V, 9AH * 4
PR5000ELCDRTXL5U	5000VA/4000W	01:18:00 h	00:31:00 h	00:16:00 h	00:11:00 h	12V, 9AH * 16
PR6000ELCDRTXL5U	6000VA/4500W	01:08:00 h	00:26:00 h	00:14:00 h	00:10:00 h	12V, 9AH * 16

Model	VA/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
PP800E	800VA/550W	01:10:00 h	00:19:00 h	00:10:00 h	00:07:00 h	12V, 8AH * 2
PP1100E	1100VA/700W	00:40:00 h	00:18:00 h	00:10:00 h	00:07:00 h	12V, 10AH * 2
PP1500TE	1500VA/1000W	00:30:00 h	00:11:00 h	00:06:00 h	00:03:00 h	12V, 10AH * 2
PP1500E	1500VA/1000W	00:38:00 h	00:15:00 h	00:08:00 h	00:05:00 h	12V, 7AH * 4
PP2200E	2200VA/1500W	00:28:00 h	00:12:00 h	00:07:00 h	00:04:00 h	12V, 9AH * 4

Model	VA/W	Rating 25% Load	Rating 50% Load	Rating 75% Load	Rating 100% Load	Battery Type
OL6000ELCDRTXL3U	6000VA/4800W	00:31:00 h	00:15:00 h	00:08:00 h	00:05:00 h	12V, 7AH * 20
OL8000ELCDRTXL3U	8000VA/6400W	00:31:00 h	00:15:00 h	00:09:00 h	00:06:00 h	12V, 9AH * 20
OL10000ELCDRTXL3U	10000VA/8000W	00:22:00 h	00:10:00 h	00:06:00 h	00:04:00 h	12V, 9AH * 20

Model	VA/W	25% Load	50% Load	75% Load	100% Load	Battery Type
CP900EPFCLCD	900VA/540W	00:24:00 h	00:09:00 h	00:04:00 h	00:02:00 h	12V, 8.5AH * 1
CP1300EPFCLCD	1300VA/780W	00:29:00 h	00:11:00 h	00:05:00 h	00:03:00 h	12V, 7AH * 2
CP1500EPFCLCD	1500VA/900W	00:31:00 h	00:11:00 h	00:05:00 h	00:02:00 h	12V, 8.5AH * 2