Firmware Update for Combo External Case

Main Chipset : PL-3507

OS : Win98SE/Win2000

- Step 1 . Connect your combo external case with drive to the USB port of your Computer.
- Step 2. When the combo external drive is detected by system, run the update program "ROMWriter2.1.3RS32.exe"

PL3507 ROM Writer 2.1.3 RS32 - No File Loaded	×
Enable verification	Code size: ROM size: FW ver. Vendor ID:
[Load File] Update Read ROM Exit	Chip ID:

Step3 Click on the "Load File" and select the firmware that you want to update.

Enable verifi	cation			Code size: ROM size: FW ver. Vendor ID:
oad File	Update	Read ROM	Exit	Chip ID:
啓 韓位置(]):		507B_041703	•	<u>? ×</u> • € ♂ ⊞•
A CARACTER STATE		507B_041703		and the second

Step 4 Check the "enable verification" and click on update , the program will start to update the firmware that you choice .

Step 5 After finish the update , restart your combo external case to make it effective.